


Cables and adaptors



Servo lead, gold, 0.3 mm²
Cable: 0.3 mm², 30 cm long
No. 4400 Pack of 1
No. 4401 Pack of 50



Socket lead, gold, 0.3 mm²
Cable: 0.3 mm², 30 cm long
No. 4402 Pack of 1
No. 4403 Pack of 50



Battery lead, gold, 0.3 mm²
Cable: 0.3 mm², 20 cm long
No. 4404 Pack of 1
No. 4405 Pack of 50



Servo extension lead, 20 cm
Cable: 0.3 mm², 20 cm gold
No. 4385 Pack of 1



Servo extension lead, 40 cm
Cable: 0.3 mm², 40 cm gold
No. 4386 Pack of 1



Servo extension lead, 100 cm
Cable: 0.3 mm², 100 cm gold
No. 4387 Pack of 1



Servo cable, twisted, 0.14 mm²
For installation in wings
No. F 1452 400 m
No. F 1452005 5 m



Transmitter charge lead
Banana plugs / NES-J plug,
100 cm long
No. F 1415 Pack of 1



Receiver battery charge lead
Banana plugs / 3-pin micro-
connector
Cable: 0.25 mm², 100 cm long
No. F 1416 Pack of 1



Direct charge lead, international
Banana plugs / Molex plug
Cable: 0.14 mm², 100 cm long
For batteries No. 4377 and 4414
No. 8263 Pack of 1



Direct charge lead, F-series
Banana plugs / Molex plug
Cable: 0.14 mm², 100 cm long
No. 8262 Pack of 1



BEC charge lead
Banana plugs / BEC plug
Cable: 0.3 mm², 100 cm long
No. F 1418 Pack of 1

Cables and adaptors



AMP charge lead
Banana plugs / AMP Mate-N-Lok
plug
Cable 1 mm², 30 cm long
No. 8253 Pack of 1



JST/TAM charge lead
Banana plugs / JST-TAM plug
Cable 1 mm², 30 cm long
No. 8192 Pack of 1



Universal charge lead
Banana plugs / crocodile clips
Cable: 0.75 mm², 100 cm long
No. 8259 Pack of 1




**Transmitter battery charge
lead**
Banana plugs / DIN plug
Cable: 0.25 mm², 100 cm long
No. F 1417 Pack of 1



Lead/acid battery charge lead
Banana plugs / 4.8 mm Faston
plugs
Cable: 0.75 mm², 100 cm long
No. 8137 Pack of 1



Standard switch harness
3-pin micro-plug and socket, no
charge socket
No. F 1408 Pack of 1



Switch harness
3-pin micro-plug and socket,
with charge socket
No. F 1407 Pack of 1



BEC switch harness
3-pin micro-plug and BEC socket,
no charge socket
No. F 1401 Pack of 1



BEC plug lead
Cable approx. 0.14 mm², 15 cm
long
No. F 1410 Pack of 1
No. F 1410005 Pack of 5



BEC socket lead
Cable approx. 0.14 mm², 15 cm
long
No. F 1409 Pack of 1
No. F 1409005 Pack of 5



BEC extension lead
Battery box - switch harness
extension, 10 cm long
No. 8038 Pack of 1



Power lead, 50 mm
Connects receiver and battery
directly, no switch harness requir-
ed
No. F 1411 Pack of 1